

Система автоматизации TROVIS 6600

CPU-модуль

TROVIS 6610

SAMSON



MEMBER OF
ASHRAE **BACnet**
INTEREST GROUP EUROPE

Инструкция по монтажу и эксплуатации

EB 6610 RU

Версия программного обеспечения x.xx

Редакция июнь 2010



Примечания и их значение



ОПАСНОСТЬ!

Опасные ситуации, которые могут привести к смерти или тяжёлым травмам



ВНИМАНИЕ!

Предупреждает о материальном ущербе и выходе оборудования из строя



ПРЕДУПРЕЖДЕНИЕ!

Ситуации, которые могут привести к смерти или тяжёлым травмам



Примечание:

Дополнительная информация



Рекомендация:

Практические советы

1	Общие указания по безопасности	4
2	Общие сведения о системе автоматизации TROVIS 6600	5
2.1	Конфигурация системы	5
2.2	Количественные параметры	6
2.3	Протяжённость сети (без повторителей, хабов и т. д.)	7
2.4	Кабели	7
2.5	Напряжение питания	7
3	Рекомендации по работе с CPU-модулем TROVIS 6610	8
3.1	Настройки сети	8
4	Технические характеристики	9
5	Монтаж	13
5.1	Монтажные размеры	15
6	Электрические соединения	16
6.1	Питание	16
6.2	Расчётные параметры электропитания	17
6.3	Назначение клемм	18
7	Лицензии	21
8	Сертификаты VACnet	36

**Внимание:**

CPU-модуль TROVIS 6610 является компонентом системы автоматизации TROVIS 6600.

*Интеграция CPU-модуля TROVIS 6610 с прочими компонентами системы автоматизации TROVIS 6600 (I/O-модули TROVIS 6620, I-модуль TROVIS 6625, веб-терминал TROVIS 6615) подробно описана в **Руководстве по интеграции системы АВ 6600**.*

Данное руководство включено в онлайн-документацию программного обеспечения „Графическое проектирование“ TROVIS 6690 и может быть предоставлено по запросу.

1 Общие указания по безопасности

- Монтаж и ввод в эксплуатацию системы автоматизации TROVIS 6610 должны осуществлять только специалисты, имеющие право на проведение монтажных, пусконаладочных работ и эксплуатацию такого оборудования. Под специалистами в настоящей инструкции подразумеваются лица, которые на основе своего специального образования и опыта, а также знаний действующих норм и стандартов, регламентирующих их работу, способны предусмотреть возможные угрозы безопасности персонала.
- Система автоматизации TROVIS 6610 предназначена для использования в силовых электроустановках. При подключении и обслуживании необходимо соблюдать действующие нормы техники безопасности.
- Должны быть обеспечены специальная транспортировка и хранение таких приборов.

2 Общие сведения о системе автоматизации TROVIS 6600

Система автоматизации TROVIS 6600 состоит из автономных автоматических станций, которые, в свою очередь, состоят из CPU-модуля TROVIS 6610, I/O-модулей TROVIS 6620, I-модулей TROVIS 6625 и – дополнительно – веб-терминала TROVIS 6615. Визуализация осуществляется, как правило, в операционной системе Windows®.

Вся система позволяет обрабатывать свыше 20 000 физических параметров. I/O-модули TROVIS 6620 и I-модули TROVIS 6625 используются автономно. Они связываются с CPU-модулем TROVIS 6610 посредством RS-485. CPU-модули TROVIS 6610 взаимодействуют между собой, а также с ведущей станцией при помощи сети Ethernet (BACnet/IP, BACnet/PTP, TCP/IP или Modbus).

Высокий уровень универсальности модулей обеспечивает невысокие по стоимости решения и позволяет с лёгкостью внедрять DDC-концепции с высокой степенью децентрализации.

2.1 Конфигурация системы

Модули системы	
Регулирующая станция	TROVIS-LS
Модули управления	TROVIS-B5
CPU-модуль	TROVIS 6610 (различные варианты)
I/O-модуль	TROVIS 6620 (различные варианты)
I-модуль	TROVIS 6625
Веб-терминал	TROVIS 6615
Программное обеспечение	
Операционная система	как правило, Windows®
Визуализация процесса	например, InTouch от Wonderware
Графическое проектирование	TROVIS 6690
DA-сервер	TROVIS 6691
OPC-сервер	TROVIS 6692
Комплектующие	
Оконцовка шины	1400-9561 (2x в комплекте поставки)
Однопортовый разветвитель шин	1400-6169
Четырёхпортовый разветвитель шин	1400-7140

Основной кабель Modbus	1400-9748
Дополнительный кабель Modbus	1400-9749
Последовательный соединительн. кабель	1400-9750
Кабельный конвертер для двухпроводной цепи	1400-8800
Кабельный конвертер для четырёхпроводной цепи	1400-7308
Соединительные клеммы TROVIS 6610	1991-0133
Соединительные клеммы TROVIS 6620	1991-0134

2.2 Количественные параметры

Модули
32 CPU-модуля TROVIS 6610 на установку 32 I/O-модуля TROVIS 6620 / I-модуля TROVIS 6625 на один CPU-модуль TROVIS 6610
CPU-модуль TROVIS 6610
40 физических точек замера, в том числе: 20 универсальных устройств ввода, каждый настраивается индивидуально как <ul style="list-style-type: none"> – аналоговый вход: Pt 1000/–40 до 160 °C / 0 до 2000 Ω; начиная с версии TROVIS 6610-0001 также от 0 до 10 В – дискретный вход, в т. ч. канал 1 и 2 как счётный вход до 1 кГц (1:1) 12 дискретных выходов · 2 А, 250 В AC (индуктивный) 8 аналоговых выходов · 0 ... 10 В
I/O-модуль TROVIS 6620
20 физических точек замера, в том числе: 10 универсальных устройств ввода, каждое настраивается индивидуально как <ul style="list-style-type: none"> – аналоговый вход: Pt 1000/–40 до 160 °C/0 до 2000 Ω; начиная с версии TROVIS 6620-0001 также 0 до 10 В – дискретный вход, в т. ч. канал 1 и 2 как счётный вход до 1 кГц (1:1) 6 дискретных выходов · 2 А, 250 В AC (индуктивный) 4 аналоговых выходов · 0 ... 10 В
I-модуль TROVIS 6625
20 дискретных входов

2.3 Протяжённость сети (без повторителей, хабов и т. д.)

Ethernet	100BASE-T typ. LAN
I/O-шина	1200 м

2.4 Кабели

24 В АС	1,5 мм ² жила
Ethernet	кабель не ниже 5 категории, экранированный (STP)
I/O-шина	Жу(St) Y 2 x 2 x 0,8


2.5 Напряжение питания

24 В АС, макс. 210 ВА для
– 1 CPU-модуль TROVIS 6610 и
– всего 32 I/O-модуля TROVIS 6620 и/или I-модуля TROVIS 6625

3 Рекомендации по работе с CPU-модулем TROVIS 6610

Использование CPU-модуля TROVIS 6610 возможно только при условии, что для выполнения своих задач в сфере автоматического регулирования и контроля систем жизнеобеспечения зданий он был спроектирован при помощи программного обеспечения „Графическое проектирование“ TROVIS 6690.

Кроме этого, функциональность устройства (однако, ограниченная) может быть обеспечена при использовании веб-интерфейса. Необходимый для связи с веб-сервером стандартный IP-адрес указан на типовом шильдике модуля.



3.1 Настройки сети

CPU-модуль TROVIS 6610 поставляется без программного обеспечения оборудования. MAC-адрес и IP-адрес указаны в левой части типового шильдика.

Маска подсети 255.255.0.0, шлюз не назначен. Для изменения сетевых параметров при помощи компьютера необходимо, чтобы компьютер находился в той же подсети, что и соответствующий CPU-модуль TROVIS 6610. Пример:

	CPU-модуль TROVIS 6610	Персональный компьютер или ноутбук
IP-адрес:	172.30.245.10	172.30..XXX.XXX
Маска подсети:	255.255.0.0	255.255.0.0
Шлюз:	0.0.0.0	0.0.0.0

4 Технические характеристики

Питание	
Электропитание	24 В AC (20,4 ... 27,6 В AC)
Частотный диапазон	48 ... 62 Гц
Энергопотребление	15 ВА
Соединение	резьбовой и штекерный зажим 2 pin (зелёный) поперечное сечение провода до 2,5 мм ²
Температурный диапазон	
Эксплуатация	0 ... 55 °С
Транспортировка и хранение	-20 ... 70 °С
Относительная влажность воздуха	нормальная, без отпотевания
Электромагнитная совместимость	
Уровень помех	согласно EN 61000-6-3
Помехозащищённость	согласно EN 61000-6-2
Безопасность устройства	
Класс защиты	II согласно EN 61140: 2003
Категория по перенапряжению	II согласно EN 60664-1
Степень загрязнения	2 согласно EN 60664-1
Степень защиты	IP 20 согласно EN 60529
Монтаж	
Габариты вместе с зажимами (мм)	Ш x В x Г: 185 x 130 x 60
Вес	~ 0,7 кг
Монтаж	монтаж на несущую шину (все типы DIN и EN)
Входные/выходные соединения	резьбовые и штекерные зажимы поперечное сечение провода до 2,5 мм ²

20 универсальных входов включая 2 счётных (канал 1 и 2)



Внимание:

Гальванической развязки между входами, а также с аналоговыми выходами нет!

При использовании в качестве дискретных входов:

Питание дискретных входов	внутреннее, ~ 10 В DC
Ток измерительной цепи при коротком замыкании	500 μ A
Входная нагрузка	макс. 100
Минимальная длительность импульса (1:1) (канал 1 и 2)	> 0,5 мс (< 1 кГц) > 500 мс (только для версии TROVIS 6610-0001)
Счётный импульс	со срабатыванием по положительному фронту
Минимальная длительность импульса (канал 3 ... 20)	1 с
Светодиод на модуле для счётных входов	ВКЛ, при замыкании контакта или < 0,4 В ВЫКЛ, при размыкании контакта или > 4 В
Светодиод на модуле для дискретных входов	ВКЛ, при замыкании контакта или < 0,05 В ВЫКЛ, при размыкании контакта или > 1 В

При использовании в качестве аналоговых входов:

Датчик

Тип датчика	Pt 1000 в двухпроводном соединении
Входной диапазон	-40 ... +160 °C
Разрешение	10 бит
Точность	< 0,5 % от диапазона измерений
Влияние температуры	< 0,1 % от диапазона измерений на 10 К
Измерительный ток	500 μ A

Сопротивление

Входной диапазон	0 ... 2000 Ω , двухпроводное соединение
Разрешение	10 бит
Точность	< 0,1 % от диапазона измерений
Влияние температуры	< 0,05 % от диапазона измерений на 10 К
Измерительный ток	500 μ A

Напряжение (начиная с версии TROVIS 6610-0001)	
Входной диапазон	0 ... 10 В DC
Разрешение	10 бит
Точность	< 0,5 % от диапазона измерений
Влияние температуры	< 0,04 % от диапазона измерений на 10 К
Измерительный ток	10 кΩ
12 дискретных выходов	
Нагрузочная способность реле	250 В AC, 2 А индуктивная нагрузка 250 В AC, 3 А омическая нагрузка
8 аналоговых выходов	
Выходной диапазон	0 ... 10 В DC
Разрешение	10 бит
Точность	< 0,5 % от диапазона измерений
Влияние температуры	< 0,03 % от диапазона измерений на 10 К
Допустимая нагрузка	> 3,3 к
Ток короткого замыкания	5,5 мА
Индикация	
Светодиодная индикация состояния	дискретный вход и выход, рабочий процесс CPU и его нарушения, связь (Rx/Tx) для каждого интерфейса

Интерфейсы	
Уровень управления/CPU-модули TROVIS 6610	
Спецификация	согласно IEEE 802.3
Скорость передачи	10/100 Мбит/с
Протокол	TCP/IP
Соединение	RJ-45, 8-полюсн.
I/O-шина	
Спецификация	RS-485 2-жильный, нечувствительный к полярности
Гальваническая развязка	да
Скорость передачи (кБит/с)	9.6, 19.2, 38.4, 57.6, 115.2
Протокол	SAMSON
Соединение	3-pin штекерно-разъёмные клеммы (зелёного цвета) сечение провода до 2,5 мм ²
RS-232	
Спецификация	RS-232 с управляющими линиями RTS/CTS
Гальваническая развязка	нет
Скорость передачи (кБит/с)	9.6, 19.2, 38.4, 57.6, 115.2
Соединение	RJ 45, 8-полюсн.
Modbus	
Спецификация	RS-485, 4-жильн.; 2-жильн. через перемычку
Гальваническая развязка	да
Скорость передачи (кБит/с)	9.6, 19.2, 38.4, 57.6, 115.2
Протокол	Modbus-RTU, Master или Slave
Соединение	RJ-45, 8-полюсн.
USB	
Спецификация	2 x USB 2.0 Full speed 12 Мбит/с, флеш-накопитель, модем (USB Mass Storage, USB CDC/ACM)

5 Монтаж

- Перед монтажом CPU-модуля TROVIS 6610 следует записать IP-адрес модуля (типовой шильдик, см. рис. 1, стр. 8), поскольку в дальнейшем он потребуется для проектирования.

Конфигурация



Внимание:


- В версии TROVIS 6610-0001 при помощи DIP-переключателей можно задать назначение универсального входа, а именно: дискретный вход, вход датчика, сопротивления или потенциальный вход.
- У других версий универсальный вход нельзя использовать как потенциальный вход, поэтому конфигурация не требуется.
- У более новых версий конфигурация осуществляется при помощи «Графического проектирования» TROVIS 6690.

Конфигурирование модуля выполняется при помощи DIP-переключателей, расположенных на тыльной стороне устройства, поэтому данную операцию следует выполнять до монтажа модуля.

Для каждого универсального входа конфигурирование выполняется отдельно. Конфигурация универсальных входов выполняется в направлении слева направо (цифры 1 ... 10): входы 1 ... 10 на первом блоке переключателей и входы 11 ... 20 на втором.

Положение переключателей:

- ON: задаёт назначение универсального входа в качестве дискретного, потенциального входа или входа сопротивления
- OFF: задаёт назначение универсального входа в качестве потенциального входа




Монтаж

При монтаже модулей необходимо учесть следующее:

- Все модули предназначены для монтажа на несущую шину TS 35.
- Между зажимами модуля и кабельным каналом необходимо предусмотреть расстояние не менее 30 мм (см. рис. 3)!
- Монтаж модуля обычно выполняется в отдельном шкафу КИП.
- Вставьте модули сверху на несущую шину, используя фиксаторы, и надавите.

Установка непосредственно на исполнительный механизм также возможна при условии, что обеспечена достаточная защита при помощи разделительной перегородки.



Демонтаж

- Отожмите фиксаторы на нижней стороне модуля при помощи подходящей отвёртки.
- Теперь модуль отсоединён от несущей шины, и его можно снять.

5.1 Монтажные размеры




Рис. 3: Монтажные размеры CPU-модуля TROVIS 6610

6 Электрическое соединение

6.1 Питание

Система автоматизации TROVIS 6600 питается от сети 24 В AC.

Электропитание следует рассчитывать в зависимости от потребляемой мощности всех подключённых модулей (см. раздел 6.2).

Для электропроводки следует использовать двойные кабельные зажимы, чтобы при отделении одного из модулей остальные продолжали получать питание (см. рис. 5).

! **ВНИМАНИЕ!**

*Опасность повреждения модулей при неправильном соединении клемм!
Не подключайте клеммы заземления между модулями!*



Практическая рекомендация:

Во избежание перенапряжений SAMSON рекомендует использовать защитные разрядники.




Рис. 4: Схема электропитания 24 В AC
(показаны 1 x CPU-модуль TROVIS 6610 и 2 x I/O-модуля TROVIS 6620)

6.2 Расчётные параметры электропитания

К каждому CPU-модулю TROVIS 6610 можно подключить до 32 I/O-модулей TROVIS 6620 и/или I-модулей TROVIS 6625. Напряжение электропитания всех модулей 24 В AC.

Энергопотребление отдельных модулей

Модуль	Напряжение	Энергопотребление
CPU-модуль TROVIS 6610	24 В AC	15 ВА
I/O-модуль TROVIS 6620	24 В AC	6 ВА
I-модуль TROVIS 6625	24 В DC	8 ВА

Суммарная мощность всех подключённых модулей

Тип	Количество	Энергопотребление	Суммарная мощность
CPU-модуль TROVIS 6610	...	15 ВА	... ВА
I/O-модуль TROVIS 6620	...	6 ВА	... ВА
I-модуль TROVIS 6625	...	8 ВА	... ВА
		сумма	... ВА
		10 % резерв	... ВА
		Всего	... ВА

Падение напряжения в сети питания

Чем больше отбираемая мощность из сети электропитания, тем больше в ней падает напряжение или мощность. Падение напряжения рассчитывается следующим образом:

$$U_{RL} = \frac{2 \cdot L \cdot P}{\kappa \cdot A \cdot U_S}$$

U_{RL} : падение напряжения в прямой и обратной линии [В]

L : длина линии электропитания [м]

P : мощность, отбираемая из линии электропитания [ВА]

κ : постоянная материала (каппа); для меди 57 [м/Ω • мм²]

A : поперечное сечение провода [мм²]

U_S : напряжение питания системы; здесь 24 В

Рекомендуемая длина линии при высокой мощности

Чтобы обеспечить напряжение питания системы, необходимо учитывать нижний предел допуска трансформатора, а также нижний предел допуска системы.

$$L_{\max} = \frac{U_{RL} \cdot \kappa \cdot A \cdot U_{\text{Trafo}}}{2 \cdot P}$$

L_{\max} : макс. допустимая длина линии (в одном направлении)

U_{RL} : допустимое падение напряжения (здесь 3,6 В)

κ : постоянная материала (каппа); для меди 57 [м/Ω · мм²]

A : сечение провода [мм²]

U_{Trafo} : вторичное напряжение трансформатора (24 В AC)

P : потребляемая мощность системы (потребителя)

6.3 Назначение клемм

Присоединение выполняется при помощи штекерно-резьбовых клемм с поперечным сечением 2,5 мм²

Клемма	Канал	Соединения CPU-модуля TROVIS 6610
1	1	UE/ZE1
2		GND
3	2	UE/ZE2
4	3	UE
5		GND
6	4	UE
7	5	UE
8		GND
9	6	UE
10	7	UE
11		GND
12	8	UE
13	9	UE
14		GND
15	10	UE
16	11	UE

Клемма	Канал	Соединения CPU-модуля TROVIS 6610
17		GND
18	12	UE
19	13	UE
20		GND
21	14	UE
22	15	UE
23		GND
24	16	UE
25	17	UE
26		GND
27	18	UE
28	19	UE
29		GND
30	20	UE
<hr/>		
A		RX/TX A
B		RX/TX B
S		экран
<hr/>		
24 В AC	24 В AC 15 ВA	питание
<hr/>		
31	21	AA
32		GND
33	22	AA
34	23	AA
35		GND
36	24	AA
37	25	AA
38		GND
39	26	AA
40	27	AA
41		GND
42	28	AA

Клемма	Канал	Соединения CPU-модуля TROVIS 6610
43	29	ВА
44		питание каналов 29 и 30
45	30	ВА
46	31	ВА
47		питание каналов 31 и 32
48	32	ВА
49	33	ВА
50		питание каналов 33 и 34
51	34	ВА
52	35	ВА
53		питание каналов 35 и 36
54	36	ВА
55	37	ВА
56		питание каналов 37 и 38
57	38	ВА
58	39	ВА
59		питание каналов 39 и 40
60	40	ВА

7 Лицензии

Технологии программного обеспечения и программы, используемые в CPU-модуле TROVIS 6610, частично связаны с приведёнными ниже лицензиями. Исходный код компонентов программного обеспечения CPU-модуля TROVIS 6610, связанных с данными лицензиями может быть предоставлен SAMSON по запросу, его также можно найти в интернете по адресу ► www.samson.de/support/deser031.htm.

GNU GENERAL PUBLIC LICENCE

Version 2, June 1991

Copyright (C) 1989, 1991 Free Software Foundation, Inc.,
51 Franklin Street, Fifth Floor, Boston, MA 02110-1301 USA

Everyone is permitted to copy and distribute verbatim copies
of this license document, but changing it is not allowed.

Preamble

The licenses for most software are designed to take away your freedom to share and change it. By contrast, the GNU General Public License is intended to guarantee your freedom to share and change free software—to make sure the software is free for all its users. This General Public License applies to most of the Free Software Foundation's software and to any other program whose authors commit to using it. (Some other Free Software Foundation software is covered by the GNU Lesser General Public License instead.) You can apply it to your programs, too.

When we speak of free software, we are referring to freedom, not price. Our General Public Licenses are designed to make sure that you have the freedom to distribute copies of free software (and charge for this service if you wish), that you receive source code or can get it if you want it, that you can change the software or use pieces of it in new free programs; and that you know you can do these things.

To protect your rights, we need to make restrictions that forbid anyone to deny you these rights or to ask you to surrender the rights. These restrictions translate to certain responsibilities for you if you distribute copies of the software, or if you modify it.

For example, if you distribute copies of such a program, whether gratis or for a fee, you must give the recipients all the rights that you have. You must make sure that they, too, receive or can get the source code. And you must show them these terms so they know their rights.

We protect your rights with two steps: (1) copyright the software, and (2) offer you this license which gives you legal permission to copy, distribute and/or modify the software.

Also, for each author's protection and ours, we want to make certain that everyone understands that there is no warranty for this free software. If the software is modified by someone else and passed on, we want its recipients to know that what they have is not the original, so that any problems introduced by others will not reflect on the original authors' reputations.

Finally, any free program is threatened constantly by software patents. We wish to avoid the danger that redistributors of a free program will individually obtain patent licenses, in effect making the program proprietary. To prevent this, we have made it clear that any patent must be licensed for everyone's free use or not licensed at all.

The precise terms and conditions for copying, distribution and modification follow.

TERMS AND CONDITIONS FOR COPYING, DISTRIBUTION AND MODIFICATION

0. This License applies to any program or other work which contains a notice placed by the copyright holder saying it may be distributed under the terms of this General Public License. The "Program", below, refers to any such program or work, and a "work based on the Program" means either the Program or any derivative work under copyright law: that is to say, a work containing the Program or a portion of it, either verbatim or with modifications and/or translated into another language. (Hereinafter, translation is included without limitation in the term "modification".) Each licensee is addressed as "you".

Activities other than copying, distribution and modification are not covered by this License; they are outside its scope. The act of running the Program is not restricted, and the output from the Program is covered only if its contents constitute a work based on the Program (independent of having been made by running the Program). Whether that is true depends on what the Program does.

1. You may copy and distribute verbatim copies of the Program's source code as you receive it, in any medium, provided that you conspicuously and appropriately publish on each copy an appropriate copyright notice and disclaimer of warranty; keep intact all the notices that refer to this License and to the absence of any warranty; and give any other recipients of the Program a copy of this License along with the Program.

You may charge a fee for the physical act of transferring a copy, and you may at your option offer warranty protection in exchange for a fee.

2. You may modify your copy or copies of the Program or any portion of it, thus forming a work based on the Program, and copy and distribute such modifications or work under the terms of Section 1 above, provided that you also meet all of these conditions:

- a)** You must cause the modified files to carry prominent notices stating that you changed the files and the date of any change.
- b)** You must cause any work that you distribute or publish, that in whole or in part contains or is derived from the Program or any part thereof, to be licensed as a whole at no charge to all third parties under the terms of this License.
- c)** If the modified program normally reads commands interactively when run, you must cause it, when started running for such interactive use in the most ordinary way, to print or display an announcement including an appropriate copyright notice and a notice that there is no warranty (or else, saying that you provide a warranty) and that users may redistribute the program under these conditions, and telling the user how to view a copy of this License. (Exception: if the Program itself is interactive but does not normally print such an announcement, your work based on the Program is not required to print an announcement.)

These requirements apply to the modified work as a whole. If identifiable sections of that work are not derived from the Program, and can be reasonably considered independent and separate works in themselves, then this License, and its terms, do not apply to those sections when you distribute them as separate works. But when you distribute the same sections as part of a whole which is a work based on the Program, the distribution of the whole must be on the terms of this License, whose permissions for other licensees extend to the entire whole, and thus to each and every part regardless of who wrote it.

Thus, it is not the intent of this section to claim rights or contest your rights to work written entirely by you; rather, the intent is to exercise the right to control the distribution of derivative or collective works based on the Program.

In addition, mere aggregation of another work not based on the Program with the Program (or with a work based on the Program) on a volume of a storage or distribution medium does not bring the other work under the scope of this License.

3. You may copy and distribute the Program (or a work based on it, under Section 2) in object code or executable form under the terms of Sections 1 and 2 above provided that you also do one of the following:

- a)** Accompany it with the complete corresponding machine-readable source code, which must be distributed under the terms of Sections 1 and 2 above on a medium customarily used for software interchange; or,
- b)** Accompany it with a written offer, valid for at least three years, to give any third party, for a charge no more than your cost of physically performing source distribution, a complete

machine-readable copy of the corresponding source code, to be distributed under the terms of Sections 1 and 2 above on a medium customarily used for software interchange; or,

c) Accompany it with the information you received as to the offer to distribute corresponding source code. (This alternative is allowed only for noncommercial distribution and only if you received the program in object code or executable form with such an offer, in accord with Subsection b above.)

The source code for a work means the preferred form of the work for making modifications to it. For an executable work, complete source code means all the source code for all modules it contains, plus any associated interface definition files, plus the scripts used to control compilation and installation of the executable. However, as a special exception, the source code distributed need not include anything that is normally distributed (in either source or binary form) with the major components (compiler, kernel, and so on) of the operating system on which the executable runs, unless that component itself accompanies the executable.

If distribution of executable or object code is made by offering access to copy from a designated place, then offering equivalent access to copy the source code from the same place counts as distribution of the source code, even though third parties are not compelled to copy the source along with the object code.

4. You may not copy, modify, sublicense, or distribute the Program except as expressly provided under this License. Any attempt otherwise to copy, modify, sublicense or distribute the Program is void, and will automatically terminate your rights under this License. However, parties who have received copies, or rights, from you under this License will not have their licenses terminated so long as such parties remain in full compliance.

5. You are not required to accept this License, since you have not signed it. However, nothing else grants you permission to modify or distribute the Program or its derivative works. These actions are prohibited by law if you do not accept this License. Therefore, by modifying or distributing the Program (or any work based on the Program), you indicate your acceptance of this License to do so, and all its terms and conditions for copying, distributing or modifying the Program or works based on it.

6. Each time you redistribute the Program (or any work based on the Program), the recipient automatically receives a license from the original licensor to copy, distribute or modify the Program subject to these terms and conditions. You may not impose any further restrictions on the recipients' exercise of the rights granted herein. You are not responsible for enforcing compliance by third parties to this License.

7. If, as a consequence of a court judgment or allegation of patent infringement or for any other reason (not limited to patent issues), conditions are imposed on you (whether by court order, agreement or otherwise) that contradict the conditions of this License, they do not

excuse you from the conditions of this License. If you cannot distribute so as to satisfy simultaneously your obligations under this License and any other pertinent obligations, then as a consequence you may not distribute the Program at all. For example, if a patent license would not permit royalty-free redistribution of the Program by all those who receive copies directly or indirectly through you, then the only way you could satisfy both it and this License would be to refrain entirely from distribution of the Program.

If any portion of this section is held invalid or unenforceable under any particular circumstance, the balance of the section is intended to apply and the section as a whole is intended to apply in other circumstances.

It is not the purpose of this section to induce you to infringe any patents or other property right claims or to contest validity of any such claims; this section has the sole purpose of protecting the integrity of the free software distribution system, which is implemented by public license practices. Many people have made generous contributions to the wide range of software distributed through that system in reliance on consistent application of that system; it is up to the author/donor to decide if he or she is willing to distribute software through any other system and a licensee cannot impose that choice.

This section is intended to make thoroughly clear what is believed to be a consequence of the rest of this License.

8. If the distribution and/or use of the Program is restricted in certain countries either by patents or by copyrighted interfaces, the original copyright holder who places the Program under this License may add an explicit geographical distribution limitation excluding those countries, so that distribution is permitted only in or among countries not thus excluded. In such case, this License incorporates the limitation as if written in the body of this License.

9. The Free Software Foundation may publish revised and/or new versions of the General Public License from time to time. Such new versions will be similar in spirit to the present version, but may differ in detail to address new problems or concerns.

Each version is given a distinguishing version number. If the Program specifies a version number of this License which applies to it and "any later version", you have the option of following the terms and conditions either of that version or of any later version published by the Free Software Foundation. If the Program does not specify a version number of this License, you may choose any version ever published by the Free Software Foundation.

10. If you wish to incorporate parts of the Program into other free programs whose distribution conditions are different, write to the author to ask for permission. For software which is copyrighted by the Free Software Foundation, write to the Free Software Foundation; we sometimes make exceptions for this. Our decision will be guided by the two goals of preserving the free status of all derivatives of our free software and of promoting the sharing and reuse of software generally.

NO WARRANTY

11. BECAUSE THE PROGRAM IS LICENSED FREE OF CHARGE, THERE IS NO WARRANTY FOR THE PROGRAM, TO THE EXTENT PERMITTED BY APPLICABLE LAW. EXCEPT WHEN OTHERWISE STATED IN WRITING THE COPYRIGHT HOLDERS AND/OR OTHER PARTIES PROVIDE THE PROGRAM "AS IS" WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESSED OR IMPLIED, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. THE ENTIRE RISK AS TO THE QUALITY AND PERFORMANCE OF THE PROGRAM IS WITH YOU. SHOULD THE PROGRAM PROVE DEFECTIVE, YOU ASSUME THE COST OF ALL NECESSARY SERVICING, REPAIR OR CORRECTION.

12. IN NO EVENT UNLESS REQUIRED BY APPLICABLE LAW OR AGREED TO IN WRITING WILL ANY COPYRIGHT HOLDER, OR ANY OTHER PARTY WHO MAY MODIFY AND/OR REDISTRIBUTE THE PROGRAM AS PERMITTED ABOVE, BE LIABLE TO YOU FOR DAMAGES, INCLUDING ANY GENERAL, SPECIAL, INCIDENTAL OR CONSEQUENTIAL DAMAGES ARISING OUT OF THE USE OR INABILITY TO USE THE PROGRAM (INCLUDING BUT NOT LIMITED TO LOSS OF DATA OR DATA BEING RENDERED INACCURATE OR LOSSES SUSTAINED BY YOU OR THIRD PARTIES OR A FAILURE OF THE PROGRAM TO OPERATE WITH ANY OTHER PROGRAMS), EVEN IF SUCH HOLDER OR OTHER PARTY HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

END OF TERMS AND CONDITIONS

GNU LESSER GENERAL PUBLIC LICENSE

Version 2.1, February 1999

Copyright (C) 1991, 1999 Free Software Foundation, Inc.,
51 Franklin Street, Fifth Floor, Boston, MA 02110-1301 USA

Everyone is permitted to copy and distribute verbatim copies
of this license document, but changing it is not allowed.

[This is the first released version of the Lesser GPL. It also counts
as the successor of the GNU Library Public License, version 2, hence
the version number 2.1.]

Preamble

The licenses for most software are designed to take away your freedom to share and change it. By contrast, the GNU General Public Licenses are intended to guarantee your freedom to share and change free software--to make sure the software is free for all its users.

This license, the Lesser General Public License, applies to some specially designated software packages--typically libraries--of the Free Software Foundation and other authors who decide to use it. You can use it too, but we suggest you first think carefully about whether this license or the ordinary General Public License is the better strategy to use in any particular case, based on the explanations below.

When we speak of free software, we are referring to freedom of use, not price. Our General Public Licenses are designed to make sure that you have the freedom to distribute copies of free software (and charge for this service if you wish); that you receive source code or can get it if you want it; that you can change the software and use pieces of it in new free programs; and that you are informed that you can do these things.

To protect your rights, we need to make restrictions that forbid distributors to deny you these rights or to ask you to surrender these rights. These restrictions translate to certain responsibilities for you if you distribute copies of the library or if you modify it.

For example, if you distribute copies of the library, whether gratis or for a fee, you must give the recipients all the rights that we gave you. You must make sure that they, too, receive or can get the source code. If you link other code with the library, you must provide complete object files to the recipients, so that they can relink them with the library after making changes to the library and recompiling it. And you must show them these terms so they know their rights.

We protect your rights with a two-step method: (1) we copyright the library, and (2) we offer you this license, which gives you legal permission to copy, distribute and/or modify the library.

To protect each distributor, we want to make it very clear that there is no warranty for the free library. Also, if the library is modified by someone else and passed on, the recipients should know that what they have is not the original version, so that the original author's reputation will not be affected by problems that might be introduced by others.

Finally, software patents pose a constant threat to the existence of any free program. We wish to make sure that a company cannot effectively restrict the users of a free program by obtaining a restrictive license from a patent holder. Therefore, we insist that any patent license obtained for a version of the library must be consistent with the full freedom of use specified in this license.

Most GNU software, including some libraries, is covered by the ordinary GNU General Public License. This license, the GNU Lesser General Public License, applies to certain designated

libraries, and is quite different from the ordinary General Public License. We use this license for certain libraries in order to permit linking those libraries into non-free programs.

When a program is linked with a library, whether statically or using a shared library, the combination of the two is legally speaking a combined work, a derivative of the original library. The ordinary General Public License therefore permits such linking only if the entire combination fits its criteria of freedom. The Lesser General Public License permits more lax criteria for linking other code with the library.

We call this license the "Lesser" General Public License because it does Less to protect the user's freedom than the ordinary General Public License. It also provides other free software developers Less of an advantage over competing non-free programs. These disadvantages are the reason we use the ordinary General Public License for many libraries. However, the Lesser license provides advantages in certain special circumstances.

For example, on rare occasions, there may be a special need to encourage the widest possible use of a certain library, so that it becomes a de-facto standard. To achieve this, non-free programs must be allowed to use the library. A more frequent case is that a free library does the same job as widely used non-free libraries. In this case, there is little to gain by limiting the free library to free software only, so we use the Lesser General Public License.

In other cases, permission to use a particular library in non-free programs enables a greater number of people to use a large body of free software. For example, permission to use the GNU C Library in non-free programs enables many more people to use the whole GNU operating system, as well as its variant, the GNU/Linux operating system.

Although the Lesser General Public License is Less protective of the users' freedom, it does ensure that the user of a program that is linked with the Library has the freedom and the wherewithal to run that program using a modified version of the Library.

The precise terms and conditions for copying, distribution and modification follow. Pay close attention to the difference between a "work based on the library" and a "work that uses the library". The former contains code derived from the library, whereas the latter must be combined with the library in order to run.

TERMS AND CONDITIONS FOR COPYING, DISTRIBUTION AND MODIFICATION

0. This License Agreement applies to any software library or other program which contains a notice placed by the copyright holder or other authorized party saying it may be distributed under the terms of this Lesser General Public License (also called "this License"). Each licensee is addressed as "you".

A "library" means a collection of software functions and/or data prepared so as to be conveniently linked with application programs (which use some of those functions and data) to form executables.

The "Library", below, refers to any such software library or work which has been distributed under these terms. A "work based on the Library" means either the Library or any derivative work under copyright law: that is to say, a work containing the Library or a portion of it, either verbatim or with modifications and/or translated straightforwardly into another language. (Hereinafter, translation is included without limitation in the term "modification".)

"Source code" for a work means the preferred form of the work for making modifications to it. For a library, complete source code means all the source code for all modules it contains, plus any associated interface definition files, plus the scripts used to control compilation and installation of the library.

Activities other than copying, distribution and modification are not covered by this License; they are outside its scope. The act of running a program using the Library is not restricted, and output from such a program is covered only if its contents constitute a work based on the Library (independent of the use of the Library in a tool for writing it). Whether that is true depends on what the Library does and what the program that uses the Library does.

1. You may copy and distribute verbatim copies of the Library's complete source code as you receive it, in any medium, provided that you conspicuously and appropriately publish on each copy an appropriate copyright notice and disclaimer of warranty; keep intact all the notices that refer to this License and to the absence of any warranty; and distribute a copy of this License along with the Library.

You may charge a fee for the physical act of transferring a copy, and you may at your option offer warranty protection in exchange for a fee.

2. You may modify your copy or copies of the Library or any portion of it, thus forming a work based on the Library, and copy and distribute such modifications or work under the terms of Section 1 above, provided that you also meet all of these conditions:

- a)** The modified work must itself be a software library.
- b)** You must cause the files modified to carry prominent notices stating that you changed the files and the date of any change.

c) You must cause the whole of the work to be licensed at no charge to all third parties under the terms of this License.

d) If a facility in the modified Library refers to a function or a table of data to be supplied by an application program that uses the facility, other than as an argument passed when the facility is invoked, then you must make a good faith effort to ensure that, in the event an application does not supply such function or table, the facility still operates, and performs whatever part of its purpose remains meaningful.

(For example, a function in a library to compute square roots has a purpose that is entirely well-defined independent of the application. Therefore, Subsection 2d requires that any application-supplied function or table used by this function must be optional: if the application does not supply it, the square root function must still compute square roots.)

These requirements apply to the modified work as a whole. If identifiable sections of that work are not derived from the Library, and can be reasonably considered independent and separate works in themselves, then this License, and its terms, do not apply to those sections when you distribute them as separate works. But when you distribute the same sections as part of a whole which is a work based on the Library, the distribution of the whole must be on the terms of this License, whose permissions for other licensees extend to the entire whole, and thus to each and every part regardless of who wrote it.

Thus, it is not the intent of this section to claim rights or contest your rights to work written entirely by you; rather, the intent is to exercise the right to control the distribution of derivative or collective works based on the Library.

In addition, mere aggregation of another work not based on the Library with the Library (or with a work based on the Library) on a volume of a storage or distribution medium does not bring the other work under the scope of this License.

3. You may opt to apply the terms of the ordinary GNU General Public License instead of this License to a given copy of the Library. To do this, you must alter all the notices that refer to this License, so that they refer to the ordinary GNU General Public License, version 2, instead of to this License. (If a newer version than version 2 of the ordinary GNU General Public License has appeared, then you can specify that version instead if you wish.) Do not make any other change in these notices.

Once this change is made in a given copy, it is irreversible for that copy, so the ordinary GNU General Public License applies to all subsequent copies and derivative works made from that copy.

This option is useful when you wish to copy part of the code of the Library into a program that is not a library.

4. You may copy and distribute the Library (or a portion or derivative of it, under Section 2) in object code or executable form under the terms of Sections 1 and 2 above provided that you accompany it with the complete corresponding machine-readable source code, which must be distributed under the terms of Sections 1 and 2 above on a medium customarily used for software interchange.

If distribution of object code is made by offering access to copy from a designated place, then offering equivalent access to copy the source code from the same place satisfies the requirement to distribute the source code, even though third parties are not compelled to copy the source along with the object code.

5. A program that contains no derivative of any portion of the Library, but is designed to work with the Library by being compiled or linked with it, is called a "work that uses the Library". Such a work, in isolation, is not a derivative work of the Library, and therefore falls outside the scope of this License.

However, linking a "work that uses the Library" with the Library creates an executable that is a derivative of the Library (because it contains portions of the Library), rather than a "work that uses the library". The executable is therefore covered by this License.

Section 6 states terms for distribution of such executables.

When a "work that uses the Library" uses material from a header file that is part of the Library, the object code for the work may be a derivative work of the Library even though the source code is not. Whether this is true is especially significant if the work can be linked without the Library, or if the work is itself a library. The threshold for this to be true is not precisely defined by law.

If such an object file uses only numerical parameters, data structure layouts and accessors, and small macros and small inline functions (ten lines or less in length), then the use of the object file is unrestricted, regardless of whether it is legally a derivative work. (Executables containing this object code plus portions of the Library will still fall under Section 6.)

Otherwise, if the work is a derivative of the Library, you may distribute the object code for the work under the terms of Section 6. Any executables containing that work also fall under Section 6, whether or not they are linked directly with the Library itself.

6. As an exception to the Sections above, you may also combine or link a "work that uses the Library" with the Library to produce a work containing portions of the Library, and distribute that work under terms of your choice, provided that the terms permit modification of the work for the customer's own use and reverse engineering for debugging such modifications.

You must give prominent notice with each copy of the work that the Library is used in it and that the Library and its use are covered by this License. You must supply a copy of this License. If the work during execution displays copyright notices, you must include the

copyright notice for the Library among them, as well as a reference directing the user to the copy of this License. Also, you must do one of these things:

- a)** Accompany the work with the complete corresponding machine-readable source code for the Library including whatever changes were used in the work (which must be distributed under Sections 1 and 2 above); and, if the work is an executable linked with the Library, with the complete machine-readable "work that uses the Library", as object code and/or source code, so that the user can modify the Library and then relink to produce a modified executable containing the modified Library. (It is understood that the user who changes the contents of definitions files in the Library will not necessarily be able to recompile the application to use the modified definitions.)
- b)** Use a suitable shared library mechanism for linking with the Library. A suitable mechanism is one that (1) uses at run time a copy of the library already present on the user's computer system, rather than copying library functions into the executable, and (2) will operate properly with a modified version of the library, if the user installs one, as long as the modified version is interface-compatible with the version that the work was made with.
- c)** Accompany the work with a written offer, valid for at least three years, to give the same user the materials specified in Subsection 6a, above, for a charge no more than the cost of performing this distribution.
- d)** If distribution of the work is made by offering access to copy from a designated place, offer equivalent access to copy the above specified materials from the same place.
- e)** Verify that the user has already received a copy of these materials or that you have already sent this user a copy.

For an executable, the required form of the "work that uses the Library" must include any data and utility programs needed for reproducing the executable from it. However, as a special exception, the materials to be distributed need not include anything that is normally distributed (in either source or binary form) with the major components (compiler, kernel, and so on) of the operating system on which the executable runs, unless that component itself accompanies the executable.

It may happen that this requirement contradicts the license restrictions of other proprietary libraries that do not normally accompany the operating system. Such a contradiction means you cannot use both them and the Library together in an executable that you distribute.

7. You may place library facilities that are a work based on the Library side-by-side in a single library together with other library facilities not covered by this License, and distribute such a combined library, provided that the separate distribution of the work based on the Library and of the other library facilities is otherwise permitted, and provided that you do these two things:

- a)** Accompany the combined library with a copy of the same work based on the Library, uncombined with any other library facilities. This must be distributed under the terms of the Sections above.
- b)** Give prominent notice with the combined library of the fact that part of it is a work based on the Library, and explaining where to find the accompanying uncombined form of the same work.
- 8.** You may not copy, modify, sublicense, link with, or distribute the Library except as expressly provided under this License. Any attempt otherwise to copy, modify, sublicense, link with, or distribute the Library is void, and will automatically terminate your rights under this License. However, parties who have received copies, or rights, from you under this License will not have their licenses terminated so long as such parties remain in full compliance.
- 9.** You are not required to accept this License, since you have not signed it. However, nothing else grants you permission to modify or distribute the Library or its derivative works. These actions are prohibited by law if you do not accept this License. Therefore, by modifying or distributing the Library (or any work based on the Library), you indicate your acceptance of this License to do so, and all its terms and conditions for copying, distributing or modifying the Library or works based on it.
- 10.** Each time you redistribute the Library (or any work based on the Library), the recipient automatically receives a license from the original licensor to copy, distribute, link with or modify the Library subject to these terms and conditions. You may not impose any further restrictions on the recipients' exercise of the rights granted herein. You are not responsible for enforcing compliance by third parties with this License.
- 11.** If, as a consequence of a court judgment or allegation of patent infringement or for any other reason (not limited to patent issues), conditions are imposed on you (whether by court order, agreement or otherwise) that contradict the conditions of this License, they do not excuse you from the conditions of this License. If you cannot distribute so as to satisfy simultaneously your obligations under this License and any other pertinent obligations, then as a consequence you may not distribute the Library at all. For example, if a patent license would not permit royalty-free redistribution of the Library by all those who receive copies directly or indirectly through you, then the only way you could satisfy both it and this License would be to refrain entirely from distribution of the Library.

If any portion of this section is held invalid or unenforceable under any particular circumstance, the balance of the section is intended to apply, and the section as a whole is intended to apply in other circumstances.

It is not the purpose of this section to induce you to infringe any patents or other property right claims or to contest validity of any such claims; this section has the sole purpose of

protecting the integrity of the free software distribution system which is implemented by public license practices. Many people have made generous contributions to the wide range of software distributed through that system in reliance on consistent application of that system; it is up to the author/donor to decide if he or she is willing to distribute software through any other system and a licensee cannot impose that choice.

This section is intended to make thoroughly clear what is believed to be a consequence of the rest of this License.

12. If the distribution and/or use of the Library is restricted in certain countries either by patents or by copyrighted interfaces, the original copyright holder who places the Library under this License may add an explicit geographical distribution limitation excluding those countries, so that distribution is permitted only in or among countries not thus excluded. In such case, this License incorporates the limitation as if written in the body of this License.

13. The Free Software Foundation may publish revised and/or new versions of the Lesser General Public License from time to time. Such new versions will be similar in spirit to the present version, but may differ in detail to address new problems or concerns.

Each version is given a distinguishing version number. If the Library specifies a version number of this License which applies to it and "any later version", you have the option of following the terms and conditions either of that version or of any later version published by the Free Software Foundation. If the Library does not specify a license version number, you may choose any version ever published by the Free Software Foundation.

14. If you wish to incorporate parts of the Library into other free programs whose distribution conditions are incompatible with these, write to the author to ask for permission. For software which is copyrighted by the Free Software Foundation, write to the Free Software Foundation; we sometimes make exceptions for this. Our decision will be guided by the two goals of preserving the free status of all derivatives of our free software and of promoting the sharing and reuse of software generally.

NO WARRANTY

15. BECAUSE THE LIBRARY IS LICENSED FREE OF CHARGE, THERE IS NO WARRANTY FOR THE LIBRARY, TO THE EXTENT PERMITTED BY APPLICABLE LAW. EXCEPT WHEN OTHERWISE STATED IN WRITING THE COPYRIGHT HOLDERS AND/OR OTHER PARTIES PROVIDE THE LIBRARY "AS IS" WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESSED OR IMPLIED, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. THE ENTIRE RISK AS TO THE QUALITY AND PERFORMANCE OF THE LIBRARY IS WITH YOU. SHOULD THE LIBRARY PROVE DEFECTIVE, YOU ASSUME THE COST OF ALL NECESSARY SERVICING, REPAIR OR CORRECTION.

16. IN NO EVENT UNLESS REQUIRED BY APPLICABLE LAW OR AGREED TO IN WRITING WILL ANY COPYRIGHT HOLDER, OR ANY OTHER PARTY WHO MAY MODIFY AND/OR REDISTRIBUTE THE LIBRARY AS PERMITTED ABOVE, BE LIABLE TO YOU FOR DAMAGES, INCLUDING ANY GENERAL, SPECIAL, INCIDENTAL OR CONSEQUENTIAL DAMAGES ARISING OUT OF THE USE OR INABILITY TO USE THE LIBRARY (INCLUDING BUT NOT LIMITED TO LOSS OF DATA OR DATA BEING RENDERED INACCURATE OR LOSSES SUSTAINED BY YOU OR THIRD PARTIES OR A FAILURE OF THE LIBRARY TO OPERATE WITH ANY OTHER SOFTWARE), EVEN IF SUCH HOLDER OR OTHER PARTY HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

END OF TERMS AND CONDITIONS

8 Сертификаты BACnet



GRANT TO USE THE BTL-MARK

The BACnet Interest Group Europe (BIG-EU) grants

SAMSON AG

the right to use the BTL mark for BACnet
conformance tested products for the BACnet conformance of

**TROVIS
6610**

with


Firmware revision: SAMSON BACstack 1.6
BACnet protocol revision: 4
Device profile: B-BC





The right is granted according to the listing rules of the BACnet Interest Group Europe based on the test report no. 08.61.SAM.001.1 issued by WSPLab.


The right granted here to use the BTL mark is limited to the above mentioned product and firmware revision and may only be used on the product itself and product related documentation.

Dortmund, April 6th, 2008
The Executive Board of the BIG-EU


Volker Röhl


William O. Swan


Roger Braum


Gijs de Koning

BACnet® is a registered trademark of ASHRAE. BTL® is a registered trademark of the BACnet International.

WSPCert Certificate

No. BAC-0105-01

WSPCert attests the conformance of the following BACnet implementation to the BACnet standard ISO 16484-5:2012. The attested conformance refers to the BACnet Interoperability Building Blocks (IBBs) listed in the annex of this certificate.

The BACnet Building Controller (B-BC)
**TROVIS 6610 Automation Station
6610-0002**

with the software version:
SAMSON BACstack 2.0

of
SAMSON AG
Postfach 10 19 01, 60019 Frankfurt a.M., Germany

has fulfilled the requirements according to the test standard ISO 16484-6, the BTL Test Plan 12.0 and the Certification Rules of the BACnet Interest Group Europe, see **MBS Test Report No. VG 2012_7573**.

The certificate is valid
until 2015/04/01

2013/11/04

Date of initial certification



Dipl.-Ing. G. Weinmann
Head of Certification Body



WSPCert Dr.-Ing. Frank Bitter
Kapuzinerweg 7, 70374 Stuttgart, Germany,
phone: +49 (0)711 9539220, email: info@wspcert.de

Certification body
accredited by the DAkkS
according to EN 45011





Annex to Certificate No. BAC-0105-01

The certification of the BACnet Implementation
TROVIS 6610-0002 Automation Station
 of **SAMSON AG**

refers to the BACnet Interoperability Building Blocks (BIBBs) listed below. BIBBs other than listed are not part of the certification.

BACnet Interoperability Building Blocks	
DS-RP-A	Data Sharing – Read Property – A
DS-RP-B	Data Sharing – Read Property – B
DS-RPM-A	Data Sharing – Read Property Multiple – A
DS-RPM-B	Data Sharing – Read Property Multiple – B
DS-WP-A	Data Sharing – Write Property – A
DS-WP-B	Data Sharing – Write Property – B
DS-WPM-B	Data Sharing – Write Property Multiple – B
DS-COV-A	Data Sharing – COV – A
DS-COV-B	Data Sharing – COV – B
AE-N-I-B	Alarm and Event – Notification Internal – B
AE-N-E-B	Alarm and Event – Notification External – B
AE-ACK-B	Alarm and Event – Acknowledge Alarm – B
AE-ASUM-B	Alarm and Event – Alarm Summary – B
AE-ESUM-B	Alarm and Event Management – Event-Enrollment Summary – B
AE-INFO-B	Alarm and Event – Information – B
SCHED-I-B	Scheduling – Internal – B
SCHED-E-B	Scheduling – External – B
T-VMT-I-B	Trending – Viewing and Modifying Trends Internal – B
T-VMT-E-B	Trending – Viewing and Modifying Trends External – B
T-ATR-B	Trending – Automated Trend Retrieval – B
DM-DDB-A	Device Management – Dynamic Device Binding – A
DM-DDB-B	Device Management – Dynamic Device Binding – B
DM-DOB-B	Device Management – Dynamic Object Binding – B
DM-DCC-B	Device Management – Device Communication Control – B
DM-ATS-A	Device Management – Automatic Time Synchronization – A
DM-TS-A	Device Management – Time Synchronization – A
DM-TS-B	Device Management – Time Synchronization – B
DM-UTC-A	Device Management – UTC Time Synchronization – A
DM-UTC-B	Device Management – UTC Time Synchronization – B
DM-RD-B	Device Management – Reinitialize Device – B
DM-BR-B	Device Management – Backup and Restore – B
DM-R-B	Device Management – Restart – B
DM-LM-B	Device Management – List Manipulation – B
DM-OCD-B	Device Management – Object Creation and Deletion – B

AMEVArbeitskreis Maschinen- und Elektrotechnik
staatlicher und kommunaler Verwaltungen**WSP Cert**
BACnet ZERTIFIZIERUNGSSTELLE**AMEV-Testat für zertifizierte BACnet-Geräte**

1. Folgendes BACnet-Gerät ist zertifiziert nach DIN EN ISO 16484-5:

Anbieter	SAMSON AG	
Produkt Name	TROVIS 6610 Automationsstation	
Produkt Modell Nr.	6610-0002	
Standard-Geräteprofil	B-BC	BACnet Protokoll Vers. / Rev. 1.12
Firmware Revision	SAMSON BACstack 2.0	

Übertragungsmedium	<input checked="" type="checkbox"/> BACnet IP (Annex J)	<input type="checkbox"/> BACnet over LonTalk
	<input type="checkbox"/> BACnet MS/TP master	<input type="checkbox"/> BACnet MS/TP slave
	<input type="checkbox"/> MS/TP baud rates:	
	<input type="checkbox"/>	
Stat. Adresseinbindung	<input type="checkbox"/> Ja (nur bei MS/TP)	
Netzwerkoptionen	<input checked="" type="checkbox"/> BBMD	<input checked="" type="checkbox"/> Anmeldg. durch ext. Geräte
	<input type="checkbox"/> Router, Medium	
Zeichensätze	<input checked="" type="checkbox"/> UTF-8	<input checked="" type="checkbox"/> ANSI X3.4
Meldeoptionen	<input checked="" type="checkbox"/> Intrinsic Reporting	<input checked="" type="checkbox"/> Algorithmic Reporting

2. Das Gerät unterstützt die BACnet-Funktionen gemäß AMEV-Profil:

<input type="checkbox"/> AMEV-Profil AS-A (Automationsstation mit Basisausstattung)	Stand:
<input checked="" type="checkbox"/> AMEV-Profil AS-B (Automationsstation mit erweiterter Ausstattung)	Stand: V 1.1 21.08.2012
<input type="checkbox"/> AMEV-Profil	Stand:

3. Grundlagen für das AMEV-Testat:

<input checked="" type="checkbox"/> Testbericht des Testlabors MBS vom 07.11.2013 Nr. VG 2012_7573
<input checked="" type="checkbox"/> AMEV-Empfehlung BACnet 2011 V 1.1. Stand: 21.08.2012 (siehe www.amev-online.de)

4. Das AMEV-Testat gilt nur in Verbindung mit folgendem Zertifikat:


<input checked="" type="checkbox"/> Zertifikat Nr. BAC-0105 (siehe http://www.big-eu.org/conformance/eu/index.php)

(Ort, Datum)
Düsseldorf, 28.11.2013

(AMEV Obmann BACnet)

WSP CertDr.-Ing. Frank Bitter
Kapuzinerweg 7
D-70374 Stuttgart
Telefon +49 711 953922-0
Telefax +49 711 953922-66

(BACnet-Zertifizierungsstelle)





SAMSON AG · MESS- UND REGELTECHNIK
Weismüllerstraße 3 · 60314 Frankfurt am Main, Германия
Телефон: +49 69 4009-0 · Факс: +49 69 4009-1507
samson@samson.de · www.samson.de

EB 6610 RU

2015-07-24 · Russian/Русский